

MPM-1000U

USB Condenser Microphone for DAW Recording or Podcasting



The MPM-1000U is perfect for podcasting applications or recording high-quality audio directly to a computer or digital audio workstation (DAW). The built-in driver enables plug-and-play USB performance, and its smooth frequency response will put the finishing touch on any project.

Features

- Condenser microphone with USB output
- Perfect for DAW recording or podcasting applications
- Extended frequency response and low self-noise
- High speed analog to digital converter
- Solid construction

Specs

Element	Back electret condenser
Element diameter	14mm
Frequency Response	20–17,000Hz
Sensitivity	-34dB ± 2dB (0dB = 1V/Pa @ 1kHz)
Output	USB
A-D converter	48kHz / 16-bit sampling rate
Output impedance	100Ω ± 30% (at 1kHz)
Load impedance	>1kΩ
Self noise	16dBA
Max. SPL	132dB (at 1kHz <1% THD)
Signal to Noise ratio	78dB